# S5110/ART 7 LITE one line video kit

Reference: S5110/ART 7 LITE
Product code: 12205120
EAN code: 8429898022376




## Main characteristics

Soul video door panel kit with 2-wire technology.

- SOUL/1 LITE outdoor panel with 1 call button and surface-mounted installation
- Monitor ART 7 LITE/G2+ 7" hands free
- Power supply FA-G2+/LITE

## More information

**ART 7 LITE/G2+ MONITOR**
Hands-free monitor for surface installation.
7" screen with capacitive navigation buttons.
High efficiency loudspeakers.
Audio communications, video and secret door opening.
Video-spy functions, auto-start, doctor mode and do not disturb.
Intercommunication with other units of the house selectively.
Different ring tones selectable.
Connection to the entrance door pushbutton, which saves the use of the doorbell.
Dimensions: 222(W) x 154(H) x 15(D) mm.
Up to 4 monitors in the same house without additional power.
Power supply FA-G2+/LITE.
Use 12V d.c. lock release (does not include lock release).
Recommended lock release: CV-24P/UNI (20600252).

**SOUL/1 LITE PANEL**
Zamak front in graphite finish
CMOS 120º camera
**IK07** anti-vandalism and **IP44** weatherproof rating
Auto-start LEDs depending on outdoor lighting
Leds indicate the different states of the system (call in progress, communication, door opening or occupied system)
1 Metallic call button
Secret communication of audio, video and door opening
Relay output for activation of two doors
Connection to analog CCTV camera
Surface installation
VIS-SOUL **rain shield is included**
Dimensions: 90(W) x 170(H) x 27(D) mm

## Accessories

- ART 4/G2+ 4.3" hands free monitor
- ART 7H/G2+ 7" hands free monitor with inductive loop
- ART 1/G2+ hands free audio unit
- Video distributor D4L-G2+/DIN
- Door panels Multiplexer DPM-G2+
- SOB-UNI table stand
- ART 7 LITE/G2+ 7" hands free monitor
- T-ART/G2+ Phone 4 Push buttons
- D4L-G2+ small video distributor
- D2L-G2+ video distributor
- MAC-SOUL replacement frame

Visit in the website: https://www.golmar.es/products/s5110-art-7-lite

**Golmar Sistemas de Comunicación S.A.**
Silici 13 • 08940 Cornellà de Llobregat (Barcelona) • Tel: +34 934 800 696 • golmar@golmar.es • www.golmar.es