# R-TEKNA-S PLUS compact 4.3" video monitor replacement

Reference: R-TEKNA-S PLUS
Product code: 19942126
EAN code: 8429898027333



## Main characteristics

- "Plus" digital installation of CAT5 or 3 wires + coaxial cable.
- Casing manufactured in ABS RAL9003 white colour.
- 4,3" colour TFT LCD screen.
- Brightness and color adjustments.
- Detachable telephone cord with connectors.
- RJ-45 additional connector for CAT5 wiring.
- Surface installation through metal wall mounting connector.

## More information

Dip switch for alternative programming.
Privacy on audio, video and door open progresses.
On-Off push button with light indicator.
Video spy and auto switch-on functions.
Input for EL562S receiver module, that allows video signal reception through a twisted pair wires, replacing the coaxial cable.
Input for door bell apartment push button.
Different call reception tones depending where the call is coming from.
Three positions call volume regulator.
Possibility to automatically activate the lock when a call is received.
Uses the lock release push button to call to the concierge unit.
Panic call to the concierge unit and connection to a second concierge.
Background tones in the telephone handset confirm outgoing calls are in progress.
Output for activation of a SAV-90 call repeater or a SAR-12/24 relay unit during call reception.
Two programmable buttons for the activation of auxiliary devices (second camera, lights, ...), using SAR-12/24 relay units.
Selectable intercommunication between TEKNA-S PLUS units (up to five) in the same apartment. During intercom function, call from the door panel can be attended.
Use D4L-Plus/RJ45 or D6L-Plus/2H video distributors in case of CAT5 installation or D4L-Plus video distributors in case of coaxial cable installations, according to the wiring run.
The maximum number of units inside the same apartment, without additional power supplies, is three.

## Accessories

- SAV-90 call repeater
- MAC-TEKNA-35/43 replacement frame
- SOB-UNI table stand
- EL562S spare video receiver module

Visit in the website: https://www.golmar.es/products/r-tekna-s-plus

**Golmar Sistemas de Comunicación S.A.**
Silici 13 • 08940 Cornellà de Llobregat (Barcelona) • Tel: +34 934 800 696 • golmar@golmar.es • www.golmar.es